



VARIABLE/STEP ATTENUATORS

Model MGKTSX-1-XX-18-A5 DC-18GHz 2,10Watts



Rotary Step attenuators are used to adjust the power signal level by step within certain frequency range, they can also be used to adjust the test system's power level as inset attenuators, it is small with high accuracy and high stability etc.

MGKTS2-1-XX-18-A5 type rotary step attenuators' average power 2W,10W, frequency range from DC-18GHz, attenuation value 0-80dB by 1dB/ 10dB step.

MECHANICAL SPECIFICATIONS

Connectors	Female Pin	Housing	Temp Range	Dimensions	Weight
Stainless Steel	Beryllium Copper Gold Plated	Aluminum	-20°C~+85°C	0~9dB:Ø48×97mm 0~80dB:Ø48×108.5mm	0~9dB:220g 0~80dB:280g

RoHS Compliant: Yes

ELECTRICAL SPECIFICATIONS

Model Number	Frequency Range(GHz)	Attenuation Step Size	Max VSWR	Insertion Loss(dB)	Attenuation Accuracy(dB)
MGKTSX-1-9-8-A5	DC-8	0-9dB in 1dB steps	1.40	≤0.8	±0.6
MGKTSX-1-9-12.4-A5	DC-12.4		1.50	≤1.0	±0.8
MGKTSX-1-9-18-A5	DC-18		1.60	≤1.2	±1.0
MGKTSX-1-90-8-A5	0.1-8	0-90dB in 10dB steps	1.40	≤1.0	±1.5(0~60) ±2.5 or 3.5%(70~90)
MGKTSX-1-90-12.4-A5	0.1-12.4		1.50	≤1.2	
MGKTSX-1-90-18-A5	0.1-18		1.60	≤1.5	

NOMINAL IMPEDANCE: 50Ω

AVERAGE POWER: 2W,10W

PEAK POWER: 200W (5μs pulse width with 0.5% duty cycles)

CONNECTOR TYPE: SMA (F,F)

Notes:

1. Dimensions Tolerance ±5%
2. Custom designs available for other special attenuation value & accuracy